

Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Office: (765) 883-5538 | Fax: (765) 883-7505 Toll Free: (800) 888-5538

## **20 AMP POWER CONTROL RELAYS**


#### RIB2401SBC

Power Relay, 20 Amp SPDT + Override, 24 Vac/dc/120 Vac Coil, NEMA 1 Housing

# Wht/Blk 120 Vac Yel Wht/Blu 24 Vac/do MANUAL Wht/Yel AUTO OPEN 1 N/O N/C CLOSED CLOSED

#### RIB2402SBC

Power Relay, 20 Amp SPDT + Override, 24 Vac/dc/208-277 Vac Coil, NEMA 1 Housing













## **SPECIFICATIONS**

# Relays & Contact Type: One (1) SPDT Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature:  $-30 \text{ to } 140^{\circ} \text{ F}$ 

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 18ms

Relay Status: LED On = Activated

**Dimensions:** 2.390"H x 3.310"W x 1.810"D with .50" NPT Nipple **Housing Detail:** See **Housing B** in housing guide for dimensions

**Origin:** Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, UL864, C-UL

California State Fire Marshal, CE, RoHS

Housing Rating: UL Accepted for Use in Plenum, NEMA 1 Gold Flash: No

Override Switch: Yes (2)

#### **Contact Ratings:**

20 Amp Resistive @ 277 Vac 20 Amp Ballast @ 277 Vac (N/O) 10 Amp Ballast @ 277 Vac (N/C) Not rated for Electronic Ballast 10 Amp Tungsten @ 120 Vac (N/O) 770 VA Pilot Duty @ 120 Vac 1,110 VA Pilot Duty @ 277 Vac

2 HP @ 277 Vac 1 HP @ 120 Vac

#### Coil Current:

50 mA @ 18 Vac

83 mA @ 24 Vac

47 mA @ 120 Vac (RIB2401SBC)

69 mA @ 208-277 Vac (RIB2402SBC)

33 mA @ 22 Vdc 35 mA @ 24 Vdc

47 mA @ 30 Vdc

## **Coil Voltage Input:**

24 Vac/dc; 120 Vac; 50-60 Hz (RIB2401SBC) 24 Vac/dc; 208-277 Vac; 50-60 Hz (RIB2402SBC)

Drop Out =  $2.1 \,\text{Vac} / 3.8 \,\text{Vdc}$ 

Pull In = 18 Vac / 22 Vdc