


Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

# **LATCHING RELAY**


## RIBL12SB

Mechanically Latching Relay, 20 Amp SPST + True Override, 12 Vac/dc Coil, NEMA 1 Housing



### RIBL12SBM

Mechanically Latching Relay, 20 Amp SPST + True Override, 12 Vac/dc Coil, Status LED, Auxiliary Output, NEMA 1 Housing









### **SPECIFICATIONS**

# Relays & Contact Type: One (1) SPST Latching Relay, Dual Coil Expected Relay Life: 1 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 50ms Maximum Pulse Length: 30 seconds Relay Status / Auxiliary: (RIBL12SBM)

**Contact Closed:** LED On = Voltage Detected on Load Wire (RIBL12SBM) **Dimensions:** 1.70"H x 2.80"W x 1.50"D with 0.50"NPT nipple (RIBL12SB)

2.39"H x 3.31"W x 1.81"D with 0.50" NPT nipple (RIBL12SBM)

Housing Detail: See Housing A (RIBL12SB) or Housing B (RIBL12SBM)

in housing guide for dimensions

Origin: Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL60947, C-UL, CE, RoHS Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No Override Switch: Yes

#### Contact Ratings:

20 Amp Resistive @ 120-277 Vac 20 Amp Ballast @ 120-277 Vac 16 Amp Electronic Ballast @ 120-277 Vac 5540 Watt Tungsten @ 277 Vac 720 VA Pilot Duty @ 120-277 Vac 2 HP @ 277 Vac

3 HP @ 240 Vac 1.5 HP @ 120 Vac

#### Coil Current:

182 mA @ 10 Vac 250 mA @ 12 Vac 165 mA @ 10 Vdc 198 mA @ 12 Vdc 250 mA @ 15 Vdc Latch / Unlatch:

Min. 10 Vdc / 11 Vac **Auxiliary Contact:** 

3 Amp @ 30 Vac/dc max. (RIBL12SBM)

#### Notes:

- Application of voltage on latch coil (Wht/Blu & Wht/Yel) will close the contact.
- Application of voltage on unlatch coil (Wht/Red & Wht/Yel) will open the contact.
- Voltage should not be applied to the coil for more than 30 seconds.
- Auxiliary contact and status LED activate when 120-277 Vac is applied between Load (Org) wire and Load Neutral (Wht/Blk) wire. (RIBL12SBM)