


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 | Office: (765) 883-5538 | Fax: (765) 883-7505

## **WIRELESS CONTROL RELAY**

## **RIBW21BAO-EN3**

EnOcean 902 MHz Wireless Relay, Transceiver / Repeater, 20 Amp SPDT, 120-277 Vac Power Input, 0-10 Vdc Analog Output, NEMA 1 Housing



RELAY HAS BUILT-IN
REPEATER FUNCTION.
RELAY RECEIVES SIGNAL
FROM WIRELESS SWITCH
TRANSMITTER AND
REBROADCASTS THE
SIGNAL TO THE NEXT RELAY
RECEIVER.

**Contact Ratings:** 

2 HP @ 277 Vac

1 HP @ 120 Vac

**Power Input Ratings:** 

39 mA max @ 120-277Vac

**Analog Output Ratings:** 

20 Amp Resistive @ 277 Vac

20 Amp Ballast @ 277 Vac (N/O)

10 Amp Tungsten @ 120 Vac (N/O)

16 Amp Electronic Ballast @ 277 Vac (N/O)

0-10Vdc, 10mA Sourcing/50mA Sinking

10 Amp Ballast @ 277Vac (N/C)

770 VA Pilot Duty @ 120 Vac

1,110 VA Pilot Duty @ 277 Vac



## **SPECIFICATIONS**

# Relays & Contact Type: One (1) SPDT Continuous Duty Coil

**Expected Relay Life:** 10 million cycles minimum mechanical **Operating Temperature:** -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Red LED: Relay Status / Learn Mode Status (Flashing)

Dimensions: 2.39"H x 3.31"W x 1.81"D with 0.75" NPT nipple

Housing Detail: See Housing B in housing guide for demensions

Wires: 16", 600V Rated

**Approvals:** UL Listed, UL916, C-UL, RoHs **Agency Compliance:** FCCID: SZV-TCM320U

IC: 5713A-TCM320U

Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No
Override Switch: No
Frequency: 902 MHz
Receiver Sensitivity: -93 dBm typical
Conducted Power: 5 mW typical

Built-in Switch Modes: Alarm, Repeater, Delay, Dimming, Rocker, Momentary, and Toggle

Origin: Made of US and non-US parts

## Note

- Compatible with Enocean® 902 MHz Switches/Transmitters.
- Typical range: 50-150 ft.
- Open area transmission could be farther.
   Consult factory for more information.
- Repeater function only rebroadcasts original EnOcean® transmission. Up to two repeaters can be used.
- For setup instructions, see website.