


Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

10 AMP PILOT CONTROL RELAYS


RIBU1S

Pilot Relay, 10 Amp SPST-N/O + Override, 10-30 Vac/dc/120 Vac Coil, NEMA 1 Housing



RIBH1S

Pilot Relay, 10 Amp SPST-N/O + Override, 10-30 Vac/dc/208-277 Vac Coil, NEMA 1 Housing









SPECIFICATIONS

Relays & Contact Type: One (1) SPST Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing) Operate Time: 20ms

Relay Status: LED On = Activated

Dimensions: 2.39"H x 3.31"W x 1.81"D with 0.50" NPT nipple

Housing Detail: See Housing B in housing guide for dimensions

Origin: Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, C-UL, CE, RoHS

Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: Yes Override Switch: Yes

Contact Ratings:

10 Amp Resistive @ 277 Vac 480 VA Pilot Duty @ 277 Vac 480 VA Ballast @ 277 Vac Not rated for Electronic Ballast 600 Watt Tungsten @ 120 Vac (N/O) 240 Watt Tungsten @ 120 Vac (N/C)

1/3 HP @ 120-240 Vac (N/O) 1/6 HP @ 120-240 Vac (N/C) 1/4 HP @ 277 Vac (N/O)

1/8 HP @ 277 Vac (N/C)

Order Normally Closed by adding "-NC" to end of model number

Coil Current:

33 mA @ 10 Vac 13 mA @ 10 Vdc 35 mA @ 12 Vac 15 mA @ 12 Vdc 18 mA @ 24 Vdc 46 mA @ 24 Vac 55 mA @ 30 Vac 20 mA @ 30 Vdc

28 mA @ 120 Vac (RIBU1S) 39 mA @ 208-277 Vac (RIBH1S)

Coil Voltage Input:

10-30 Vac/dc; 120 Vac; 50-60 Hz (RIBU1S) 10-30 Vac/dc; 208-277 Vac; 50-60 Hz (RIBH1S) Drop Out = 2.1 Vac / 2.8 Vdc

Pull In = 9 Vac / 10 Vdc