# **RIB Building** Automation

Functional Devices, Inc.101 Commerce Drive, Sharpsville, IN 46068Email: sales@functionaldevices.comWebsite: www.functionaldevices.comToll Free: (800) 888-5538Office: (765) 883-5538Fax: (765) 883-7505


## AC POWER SUPPLIES: 120 VAC TO 24 VAC

## **PSB40AB10**

Single 40 VA Power Supply, 120 Vac to 24 Vac, 10 Amp Main Breaker, Open Bracket Panel Mount

# PSB100AB10

Single 100 VA Power Supply, 120 Vac to 24 Vac, 10 Amp Main Breaker, Open Bracket Panel Mount







CF



### **REMOVABLE TERMINAL COVER PROVIDED**

### SPECIFICATIONS

 Transformer:
 One 40 VA Split-Bobbin (PSB40AB10) One 100 VA Split-Bobbin (PSB100AB10)

 Primary:
 120 Vac

 Secondary:
 24 Vac, w/ LED Indicator

 Frequency:
 50/60 Hz

 Over Current Protection:
 Inherently Limited + Circuit Breaker (PSB40AB10) Circuit Breaker (PSB100AB10)

 24 Vac ON/OFF:
 On / Off Switch

 Main Breaker ON/OFF:
 Switch / Breaker (10 Amp) (Kills power to entire unit: Outlets, Aux. Output, & Transformer)\* Total Combined Output 9A

 Mounting: Panel mount Max. Ambient Temperature: 40° C Approvals: Class 2 (UL Approved UL5085-3), UL916, UL508, C-UL, CE, RoHS Dimensions: 5.200° H x 5.250° W x 3.750° D Origin: Made of US and non-US parts