


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 | Office: (765) 883-5538 | Fax: (765) 883-7505

FIRE ALARM RELAYS


RIB12C-FA

Polarized Relay, 10 Amp SPDT, 12 Vac/dc Coil, NEMA 1 Housing



RIB12S-FA

Polarized Relay 10 Amp SPST-N/O + Override, 12 Vac/dc Coil, NEMA 1 Housing













SPECIFICATIONS

Relays & Contact Type: One (1) SPDT Continuous Duty Coil (RIB12C-FA)

One (1) SPST Continuous Duty Coil (RIB12S-FA)

Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 6ms

Relay Status: LED On = Activated

 $\begin{array}{ll} \textbf{Dimensions:} & 1.70''\text{H x} \ 2.80''\text{W} \ x \ 1.50''\text{D} \ \text{with } 0.50'' \ \text{NPT nipple} \\ \textbf{Housing Detail:} & \text{See } \textbf{Housing A} \ \text{in housing guide for dimensions} \\ \end{array}$

Origin: Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, UL864, C-UL

California State Fire Marshal, CE, RoHS

Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No

Override Switch: No (RIB12C-FA)

Yes (RIB12S-FA)

Contact Ratings:

10 Amp General Use @ 277 Vac 10 Amp Resistive @ 30 Vdc (N/O)

7 Amp Resistive @ 30 Vdc (N/C) 1/2 HP @ 125 Vac 1 HP @ 250 Vac

1/4 HP @ 277 Vac 470 VA Pilot Duty @ 125 Vac 770 VA Pilot Duty @ 250 Vac

Coil Current:

53 mA @ 10 Vac 62 mA @ 12 Vac 29 mA @ 11 Vdc 36 mA @ 12 Vdc

RIB12S-FA-RD

· Red housing

Coil Voltage Input:

RIB12C-FA-N4

• NEMA 4X

housing, UL508 only

12 Vac/dc; 50-60 Hz Drop Out = 2 Vac / 2.5 Vdc Pull In = 9 Vac / 11 Vdc

Notes:

 \bullet Order Normally Closed by adding "NC" to end of model number (RIB12S-FA)