


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 | Office: (765) 883-5538 | Fax: (765) 883-7505

# 10 AMP TRIVOLT CONTROL RELAYS

### **RIB2401C**

TriVolt Relay, 10 Amp SPDT, 24Vac/dc or 120Vac, NEMA 1 Housing













RIB2401C-N4
• NEMA 4X housing



## **SPECIFICATIONS**

# Relays & Contact Type: One (1) SPDT Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)
Operate Time: 6ms

Relay Status: LED On = Activated

 $\begin{array}{ll} \textbf{Dimensions:} & 1.70\text{''H} \times 2.80\text{''W} \times 1.50\text{''D with } 0.50\text{''NPT nipple} \\ \textbf{Housing Detail:} & \text{See } \textbf{Housing A} \text{ in housing guide for dimensions} \end{array}$ 

**Origin:** Made of US and non-US parts

Wires: 16", 600V Rated

**Approvals:** UL Listed, C-UL, CE, RoHS (All models)

UL916 (RIB2401C)

UL864, California State Fire Marshal (RIB2401C-RD)

UL508 (RIB2401C-N4)

Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No Override Switch: No

## **Contact Ratings:**

10 Amp General Use @ 277 Vac
10 Amp Resistive @ 30 Vdc (N/O)
7 Amp Resistive @ 30 Vdc (N/C)
1/2 HP @ 125 Vac
1 HP @ 250 Vac
1/4 HP @ 277 Vac
470 VA Pilot Duty @ 125 Vac
770 VA Pilot Duty @ 250 Vac

#### **Coil Current:**

24 mA @ 20 Vac 28 mA @ 24 Vac 44 mA @ 35 Vac 28 mA @ 120 Vac 13 mA @ 20 Vdc 16 mA @ 24 Vdc 25 mA @ 35 Vdc

#### **Coil Voltage Input:**

24 Vac/dc; 120 Vac; 50-60 Hz Drop Out = 3.0 Vac / 3.8 Vdc Pull In = 20 Vac / 20 Vdc