


Functional Devices, Inc.101 Commerce Drive, Sharpsville, IN 46068Email: sales@functionaldevices.comWebsite: www.functionaldevices.comToll Free:(800) 888-5538Office:(765) 883-5538Fax:(765) 883-7505

RELAY & AC CURRENT SWITCH COMBO

RIBHX24BF

Current Switch and Relay Combination, 20 Amp SPST-N/O, Fixed, 24 Vac/dc Coil, NEMA 1 Housing













SPECIFICATIONS

 Expected Relay Life:
 10 million cycles minimum mechanical

 Operating Temperature:
 -30 to 140° F

 Humidity Range:
 5 to 95% (noncondensing)

 Operate Time:
 20ms

 Relay Status:
 Red LED On = Activated

 Current Sensor Status:
 Pink LED On = Current Over Trip Point (0.25 Amp)

 Dimensions:
 1.70"H x 2.80"W x 1.50"D with 0.50" NPT nipple

 Housing Detail:
 See Housing A in housing guide for dimensions

 Origin:
 Made of US and non-US parts

 Wire Length:
 16", 600V Rated

 Approvals:
 UL Listed, UL916, C-UL, CE, RoHS

 Housing Rating:
 UL Accepted for Use in Plenum, NEMA 1

 Gold Flash:
 No

Contact Ratings:

20 Amp Resistive @ 277 Vac 20 Amp Ballast @ 277 Vac 16 Amp Electronic Ballast @ 277 Vac (N/O) 10 Amp Tungsten @ 120 Vac (N/O) 1,110 VA Pilot Duty @ 277 Vac 770 VA Pilot Duty @ 120 Vac 2 HP @ 277 Vac 1 HP @ 120 Vac

Sensor Contact:

• When current sensor status is off (open), leakage <30 uA @ 30Vac/dc

• When current sensor status is on (closed), voltage drop < .3 Vac/dc @ .1 Amp < 1.6 Vac/dc @ .4 Amp

> **Coil Current:** 128 mA @ 24 Vac 71 mA @ 30 Vdc

Coil Voltage Input: 24 Vac/dc; 50-60 Hz Drop Out = 3 Vac Pull In = 18 Vac

 Sensor Type:
 Internal, with contact status

 Sensor Threshold:
 Fixed, .25 Amp

 Sensor Range:
 .25-20 Amps

 Sensor Feedback Output:
 Solid State Contact 30 Vac/dc, 100 mA