


Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

15 AMP PILOT CONTROL TRACK MOUNT RELAYS


RIBMNU1C

Pilot Relay, 15 Amp SPDT, 10-30 Vac/dc/ 120 Vac Coil, 2.75" Track Mount



RIBMNH1C

Pilot Relay, 15 Amp SPDT, 10-30 Vac/dc/ 208-277 Vac Coil, 2.75" Track Mount













SPECIFICATIONS

Relays & Contact Type: One (1) SPDT Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 20ms

Relay Status: LED On = Activated

Dimensions: 1.70"H x 2.75"W x 0.88"D1/1.38"D2

Housing Detail: See **Housing H** in housing guide for dimensions

Origin: Made of US and non-US parts

Track Mount: 2.750"

MT212 Mounting Track Sold Separately

Approvals: UL Listed, UL916, C-UL, CE, RoHS

UL864, California State Fire Marshal

Gold Flash: Yes Override Switch: No

Contact Ratings:

15 Amp Resistive @ 150 Vac, 28Vdc 15 Amp Inductive @ 150 Vac 10 Amp Resistive @ 120-277 Vac, 28 Vdc 480 VA Pilot Duty @ 240-277 Vac 480 VA Ballast @ 277 Vac Not rated for Electronic Ballast 600 Watt Tungsten @ 120 Vac (N/O) 240 Watt Tungsten @ 120 Vac (N/C) 1/3 HP @ 120-240 Vac (N/O) 1/6 HP @ 120-240 Vac (N/C) 1/4 HP @ 277 Vac (N/O)

Drop Out = $2.1 \, \text{Vac} / 2.8 \, \text{Vdc}$ 1/8 HP @ 277 Vac (N/C)

Coil Current:

33 mA @ 10 Vac 13 mA @ 10 Vdc 35 mA @ 12 Vac 15 mA @ 12 Vdc 46 mA @ 24 Vac 18 mA @ 24 Vdc 20 mA @ 30 Vdc 55 mA @ 30 Vac 28 mA @ 120 Vac (RIBMNU1C) 39 mA @ 208-277 Vac (RIBMNH1C)

RIBMNH1

Coil Voltage Input:

10-30 Vac/dc; 120 Vac; 50-60 Hz (RIBMNU1C) 10-30 Vac/dc; 208-277 Vac; 50-60 Hz (RIBMNH1C)

Pull In = 9 Vac / 10 Vdc