


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

## **LOW COIL INPUT RELAY**

#### RIBTE01B

Low Input/Optoisolated Relay, 20 Amp SPDT, 120 Vac Power Input, 5-25 Vac/dc Control Input, Hi/Lo Voltage Separation, NEMA 1 Housing













### **SPECIFICATIONS**

Power Input: 120 Vac, 50-60 Hz Control Input: 5-25 Vac/dc, 50-60 Hz

# Relays & Contact Type: One (1) SPDT Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature:  $-30 \text{ to } 140^{\circ} \text{ F}$ 

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 18ms

Relay Status: LED On = Activated

**Dimensions:** 4.00"H x 4.00"W x 1.81"D with 0.50" NPT nipple **Housing Detail:** See **Housing C** in housing guide for dimensions

Origin: Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, C-UL,CE, RoHS Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No Override Switch: No

#### **Contact Ratings:**

20 Amp Resistive @ 277 Vac 5 Amp Resistive @ 480 Vac 1110 VA Pilot Duty @ 277 Vac 770 VA Pilot Duty @ 120 Vac 20 Amp Ballast @ 277 Vac

16 Amp Electronic Ballast @ 277 Vac (N/O) 10 Amp Tungsten @ 120 Vac (N/O) 240 Watt Tungsten @ 120 Vac (N/C)

2 HP @ 277 Vac 1 HP @ 120 Vac

# **Power Input Ratings:**

47 mA @ 120 Vac

#### **Control Input Ratings:**

.4 mA @ 5 Vdc .9 mA @ 10 Vdc 1 mA @ 12 Vdc 2 mA @ 24 Vdc 3 mA @ 24 Vac (Non Polarized)