


Functional Devices, Inc. | 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 | Office: (765) 883-5538 | Fax: (765) 883-7505

10 AMP PILOT CONTROL RELAYS


RIBTU1C

Pilot Relay, 10 Amp SPDT, 10-30 Vac/dc/ 120 Vac Coil, Hi/Lo Voltage Separation, NEMA 1 Housing



RIBTH1C

Pilot Relay, 10 Amp SPDT, 10-30 Vac/dc/ 208-277 Vac Coil, Hi/Lo Voltage Separation, NEMA 1 Housing

















SPECIFICATIONS

Relays & Contact Type: One (1) SPDT Continuous Duty Coil

Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: $-30 \text{ to } 140^{\circ} \text{ F}$

Humidity Range: 5 to 95% (noncondensing)
Operate Time: 20ms

Relay Status: LED On = Activated

Dimensions: 4.00"H x 4.00"W x 1.81"D with 0.50" NPT nipple **Housing Detail:** See **Housing C** in housing guide for dimensions

Origin: Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, C-UL, CE, RoHS

UL864, California State Fire Marshal **Housing Rating:** UL Accepted for Use in Plenum, NEMA 1

Gold Flash: Yes Override Switch: No

Contact Ratings:

10 Amp Resistive @ 277 Vac
10 Amp Resistive @ 28 Vdc
480 VA Pilot Duty @ 240-277 Vac
480 VA Ballast @ 277 Vac
Not rated for Electronic Ballast
600 Watt Tungsten @ 120 Vac (N/O)
240 Watt Tungsten @ 120 Vac (N/C)
1/3 HP @ 120-240 Vac (N/C)
1/4 HP @ 120-240 Vac (N/C)
1/4 HP @ 277 Vac (N/O)
1/8 HP @ 277 Vac (N/C)

Coil Current:

33 mA @ 10 Vac 13 mA @ 10 Vdc 35 mA @ 12 Vac 15 mA @ 12 Vdc 46 mA @ 24 Vac 18 mA @ 24 Vdc 55 mA @ 30 Vac 20 mA @ 30 Vdc

28 mA @ 120 Vac (RIBTU1C) 39 mA @ 208-277 Vac (RIBTH1C)

Coil Voltage Input:

10-30 Vac/dc; 120 Vac; 50-60 Hz (RIBTU1C) 10-30 Vac/dc; 208-277 Vac; 50-60 Hz (RIBTH1C)

Drop Out = 2.1 Vac / 2.8 Vdc Pull In = 9 Vac / 10 Vdc